

10/100 Mbps Ethernet Repeater With 60 W Pass-Through PoE

CNFE1RPT[/PD][/M]





The ComNet CNFE1RPT is an Ethernet repeater supporting up to 60 watts of Passthrough PoE, providing a simple and cost-effective way to extend Ethernet signals beyond the standard Ethernet 328 foot (100 meter) limit. The CNFE1RPT can be used to double the distance to 656 feet (200 meters) or multiple units can be combined in series with each unit providing an additional 328 feet (100 meters). The CNFE1RPT is powered by pass-through PoE from a PoE switch or midspan injector, requiring no local power. Low power consumption ensures that maximum power is made available to the remote PD device. Available in standard configuration, which passes through the PoE to the next device, or as a /PD model, which acts as the final PoE unit in the chain and does not pass through the PoE, providing maximum flexibility for all design scenarios. The compact tube design allows for direct installation within conduit or other small enclosures. A mini size unit is also available for surface mounting, or DIN rail mounting with use of the sold-separately DINBKT4 adaptor.

FEATURES

- > Extends 10/100 Mbps Ethernet and PoE by 328 ft (100 m)
- > Extended temperature operation from -40°C to +75°C
- Pass-through PoE meets the IEEE 802.3af/at standards for Power over Ethernet
- > Powered by PoE (no local power required)
- > Supports PoE++ 60 W pass-through Power over Ethernet
- > Full unrestricted 10/100 Mbps Bandwidth
- > "Plug & Play" design requires no configuration
- Designed to meet full compliance with the environmental requirements (ambient operating temperature, mechanical shock, vibration, humidity with condensation, high-line/lowline voltage conditions and transient voltage protection) of NEMA TS-1/TS-2 and the Caltrans Specification for Traffic Signal Control Equipment.

- > LED status indicators confirm operating status
- > Designed and manufactured in the USA
- › Available in compact tube or small-size form factors
- › Lifetime Warranty

APPLICATIONS

- > Remote extension of IP devices
- CCTV systems for casinos, airports, school campuses

SPECIFICATIONS

	Et	he	rn	et
--	----	----	----	----

Ethernet		Mechanical		
Data Interface	10/100BaseT(X) Ethernet	Indicating LEDs	Ethernet Link and Activity	
	IEEE 802.3 Compliant	Circuit Board	Meets IPC Standard	
	Full Duplex or Half Duplex Electrical Ports	CNFE1RPT[/PD] Size	3.3 × 1.25 × 1.25 in (8.4 × 3.2 × 3.2 cm)	
Standards	IEEE: 802.3af PoE, 802.3at PoE+	CNFE1RPT[/PD]/M Size	3.3× 2.5 × 1.1 in (8.4 × 6.4 × 2.8 cm)	
	RFC: 768 UDP, 2068 HTTP, 793 TCP, 791 IP, 1783	Shipping Weight	<1 lbs./0.5 kg	
	TFTP, 894 IP over Ethernet, 2544 TCP/IP Packet	Environmental		
Transmission Distances ¹ Connectors Ethernet	Transmission See chart below	MTBF	>100,000 hours - 40° C to +75° C	
		Operating Temp		
	2 × RJ-45	Storage Temp	- 40° C to +80° C	
	2 × 10 +0	Relative Humidity	0% to 95% (non-condensing) ²	
Power		:		
Pass-Through Mode	Operates on PoE Power		MADE IN THE	
Power Consumption	<1W			
Protection	High Impedance PoE Pass-Through with Start-up Voltage Detection and Current Limiting			

MAXIMUM TRANSMISSION DISTANCES¹

	Maximum Range & Repeaters for PoE Power (Watts)					
PoE Source	No PoE ³	5 W	10 W	15W	20 W	25 W
15 W PoE Switch	2,625 ft 800 m (Using 7 CNFE1RPT)	1,476 ft 450 m (Using 4 CNFE1RPT)	984 ft 300 m (Using 2 CNFE1RPT)	328 ft ⁴ 100 m ⁴ (No CNFE1RPT)	N/A ⁴	N/A ⁴
30 W PoE+ Switch	2,625 ft 800 m (Using 7 CNFE1RPT)	1,969 ft 600 m (Using 5 CNFE1RPT)	1,316 ft 400 m (Using 3 CNFE1RPT)	984 ft 300 m (Using 2 CNFE1RPT)	656 ft 200 m (Using 1 CNFE1RPT)	328 ft⁴ 100 m⁴ (No CNFE1RPT)
CNGE1IPS 35 W PoE+ Injector	3,773 ft 1,150 m (Using 11 CNFE1RPT)	2,625 ft 800 m (Using 7 CNFE1RPT)	1,804 ft 550 m (Using 5 CNFE1RPT)	1,316 ft 400 m (Using 3 CNFE1RPT)	984 ft 300 m (Using 2 CNFE1RPT)	656 ft 200 m (Using 1 CNFE1RPT)

[1] Distance figures are based on 48V PSE PoE power source for PoE switches, 50V PSE PoE power source for PoE+ switches and 56V PSE PoE power source for the CNGE1IPS injector as detailed in the table. Distance figures are obtained using in-house testing mirroring installations. Factors such as cable quality, the number of connectors and splices in the cable run, the use of PoE, and environmental conditions encountered within the installation might affect the actual transmission distance and should be taken into consideration.

[3] Non-PoE applications; using a CNFE1RPT/PD model at the end of the chain

[4] Extension is not possible at this PoE power level with this particular PoE power source

ORDERING INFORMATION

Part Number	Description	Form Factor
CNFE1RPT	1 Channel 10/100 Mbps Ethernet Repeater with 60 W PoE Pass-Through	Tube
CNFE1RPT/PD	1 Channel 10/100 Mbps Ethernet Repeater	Tube
CNFE1RPT/M	1 Channel 10/100 Mbps Ethernet Repeater with 60 W PoE Pass-Through	Mini
CNFE1RPT/PD/M	1 Channel 10/100Mb Ethernet Repeater	Mini
Options	[2] Add suffix '/C' for Conformally Coated Circuit Boards to extend to condensation conditions (Extra charge, consult factory) DIN-Rail Mounting Adaptor Kit for Mini-size units only - With Mounting Hardware (sold separately, order model DINBKT4) 35W PoE+ Injector (sold separately, order model CNGE1IPS)	

In a continuing effort to improve and advance technology, product specifications are subject to change without notice.

CNFE1RPT[/PD][/M]

10/100 Mbps Ethernet Repeater With 60 W Pass-Through PoE





C Low Power Consumption



3 CORPORATE DRIVE | DANBURY, CONNECTICUT 06810 | USA | T: 203.796.5300 | F: 203.796.5303 | TECH SUPPORT: 1.888.678.9427 | INFO@COMNET.NET

8 TURNBERRY PARK ROAD | GILDERSOME | MORLEY | LEEDS, UK LS27 7LE | T: +44 (0)113 307 6400 | F: +44 (0)113 253 7462 | INFO-EUROPE@COMNET.NET 23 Feb 2018

© 2018 Communication Networks. All Rights Reserved. "ComNet" and the "ComNet Logo" are registered trademarks of Communication Networks.