



LIGHTSWITCH-LIGHTCORE-1G

Ajax LightSwitch LightCore 1-gang Jeweller. Interruptor Simple



Características

- LightCore (1-gang).
- Relé interruptor simple.
- Tecnología de comunicación Jeweller.
- Rango de comunicación por radio hasta 1.100 m.
- Funcionamiento sin cable neutro.
- Luz de fondo nocturna.
- Voltaje de alimentación 230 V~, 50 Hz.
- Consumo promedio hasta 200 mW.
- Clasificación IP20.
- Dimensiones: 76.3 × 72.3 × 29.2 mm.
- Peso: 45.95 g.

Productos Alternativos

- [LIGHTSWITCH-FRAME-2](#)
- [LIGHTSWITCH-FRAME-3](#)
- [LIGHTSWITCH-FRAME-4](#)
- [LIGHTSWITCH-FRAME-5](#)

Accesorios

- [LIGHTSWITCH-2G-GP](#)
- [LIGHTSWITCH-2G-WH](#)
- [LIGHTSWITCH-CENTER-1G-2W-BL](#)
- [LIGHTSWITCH-CENTER-1G-2W-FG](#)
- [LIGHTSWITCH-CENTER-1G-2W-GP](#)
- [LIGHTSWITCH-CENTER-1G-2W-GR](#)
- [LIGHTSWITCH-CENTER-1G-2W-IV](#)
- [LIGHTSWITCH-CENTER-1G-2W-OL](#)
- [LIGHTSWITCH-CENTER-1G-2W-OY](#)
- [LIGHTSWITCH-CENTER-1G-2W-WH](#)
- [LIGHTSWITCH-SIDE-1G-2W-GP](#)
- [LIGHTSWITCH-SIDE-1G-2W-WH](#)
- [LIGHTSWITCH-SOLO-1G-2W-BL](#)
- [LIGHTSWITCH-SOLO-1G-2W-FG](#)
- [LIGHTSWITCH-SOLO-1G-2W-GP](#)
- [LIGHTSWITCH-SOLO-1G-2W-GR](#)
- [LIGHTSWITCH-SOLO-1G-2W-IV](#)
- [LIGHTSWITCH-SOLO-1G-2W-OL](#)
- [LIGHTSWITCH-SOLO-1G-2W-OY](#)
- [LIGHTSWITCH-SOLO-1G-2W-WH](#)

<https://www.ibdglobal.com/shop/product/lightswitch-lightcore-1g-ajax-lightswitch-lightcore-1-gang-jeweller-interruptor-simple-18322>